# Single-Line Users Guide

## To place an Outgoing Call

- Lift the handset, receive dial tone
- Dial 9
- > Dial the desired Outside number

## **Extension to Extension Calling**

- Lift handset, receive dial tone
- ➤ Dial the desired extension

#### **Call Hold**

- Ask the party to hold, hit the flash button or flash the hook switch
- ➤ WAIT for the special dial tone (fast busy)
- > To retrieve the call, press the flash button or hang up and wait for the phone to ring back, original call is reconnected

#### **Consultation Hold**

- Ask the party to hold, hit the flash button or flash hook switch
- ➤ WAIT for the special (fast busy)
- ➤ Dial the desired extension, speak with the person
- When the conversation is concluded, call extension hangs up, original call is automatically reconnected

## **Transferring calls**

- Ask the party to hold, hit the flash button or flash hook switch
- ➤ WAIT for the special dial tone (fast busy)
  - > Dial the desired extension (hang up at this point to transfer without announcing)
  - > Called party answers
  - Announce that you have a call you'd like to transfer
  - ➤ If transfer is accepted, hang up (call connects)
  - > If transfer is rejected, called party hangs up (call will reconnect to your line).

#### Call pick-up

- ➤ Lift handset, receive dial tone
- ➤ Dial "\*2", thee incoming call will connect with your line

# **Call Forwarding (All Calls)**

#### To SET:

- Lift handset, receive dial tone
- ➤ Dial "\*3", WAIT for special dial tone (fast busy)
- Dial extension to which phone should be forwarded
- ➤ Receive service set tone (high-pitched tone)

# To CANCEL:

- Lift handset, receive dial tone
- ➤ Dial "\*3", receive service set tone (high-pitched tone)

### **Three-way Conference Calling**

- Ask the original party to hold, hit the flash button or flash the hook switch
- ➤ WAIT for special dial tone (fast busy)
- ➤ Dial the desired extension (or "9" and the desired outside number)
- ➤ When party answers, announce conference
- ➤ Hit the flash button or the flash hook switch and all three parties should be connected